








Smart Tools



# Better Inside, More in Sight

Milesight Technology | www.milesight.com



# QUICK START GUIDE

AI PTZ Bullet Plus Network Camera





2

## Table of Content

. Quick Installation Steps	•
P. Hardware Overview	1
B. How to Connect to Alarm Interface 5	ó
I. How to Connect the Water-proof Connector 5	ó
i. Assigning an IP Address by Using Smart Tools 6	ó
. Assigning an IP Address via Browser7	7
7. Accessing from the Web Brower 7	7




## 1. Quick Installation Steps

#### Install with junction box(A62)


Step1: Fix a sticker in the position where the camera is intended to be installed;



Step2: Unbolt the screws on the Junction Box(A62) between the front cover and rear cover and remove the front cover. Remove the tension disc on the rear cover, and cut an opening on the rubber plug and get cables through the opening then fasten the rear cover to the ceiling or wall;



Step3: Install the camera to front cover by using 4 torx screws and then reinstall the front cover from the angle near 90° to the rear cover;




Step4: Adjust the cables length, and connect the cables to corresponding interfaces and fix the tension disc. Close the junction box and fix screws at last. Please remember to plug the small rubber plug whenever the holes on the rubber plug is not in use.



#### Install to wall directly

Fix the screws to the installed wall if you don't use junction box.



#### Note:

If you need to use the SD card, please remove the screw of the rear cover and pull out the cover to get access to the SD card slot. After inserting SD card, fix the screws again.







2 www.milesight.com www.milesight.com 3



#### 2. Hardware Overview






#### Note:


- 1) Reset Button: Press "Reset" button for 5 seconds, then the device will be restored to factory default;
- 2) DC and PoE are available for Mini PTZ Bullet camera's power supply.

#### 3. How to Connect to Alarm Interface



PIN1: Alarm Output NC/NO 24V DC 1A
PIN2: Alarm Output NC/NO 24V DC 1A
PIN3: Alarm Input NC/NO ≤ 12V
PIN4: Alarm Input NC/NO ≤ 12V

## 4. How to Connect the Water-proof Connector



Network Port Connector



4 www.milesight.com www.milesight.com



Step1: Get the network cable through the screw nut, rubber ring and the screw holt:

Step2: Insert the rubber ring into the screw bolt;

Step3: Connect the screw nut to the screw bolt;


Step4: Place the O-Ring on the network port connector;


Step5: Connect the RJ45 to the network port connector, tighten the screw bolt and the connector

#### Note:

Please tightly wrapped all cable-out interface with adhesive tape at last to prevent them from water.

#### 5. Assigning an IP Address by Using Smart Tools






The steps to change the IP of cameras are as below:

- Start Smart Tools, click the IPC Tools page, then enter the device information, such as IP address, MAC address, Port number, Netmask, and Gateway, then all related Milesight network cameras in the same network that will be shown.
- 2) Select a camera or multiple cameras according to the MAC addresses.
- 3) Click "Activate" to set the password when using the cameras for the first time (Password must be 8 to 32 characters long, contain at least one number and one letter), and set three security questions (If you forget the password, you can reset the password by answering three security questions correctly).
- 4) Type the user name and password you set, change the IP address or other network values, and then click "Modify" button.
- 5) By double clicking the selected camera or the browser of interested camera, you can access the camera via web browser directly.

More usage of Smart Tools, please refer to the "Smart Tools User Manual".

#### 6. Assigning an IP Address via Browser



#### 7. Accessing from the Web Brower

The camera can be used with the most standard operating systems and browsers. The recommended browsers are Internet Explorer, Firefox, Chrome, Safari. More information about the plugin installation, please refer to the troubleshooting:

- 5. Milesight-Troubleshooting-Plugin Installation on Windows-IPC
- 6. Milesight-Troubleshooting-Plugin Installation on MAC

6 www.milesight.com www.milesight.com 7

## **AI PTZ Bullet Plus**

# Thank you for choosing Milesight Product

Milesight Technology